



Sitronix ST7920 Based modules – Interface selection

| Series     | Jumpers       | Parallel | SPI     |
|------------|---------------|----------|---------|
| CFAG12832A | Parallel Only |          |         |
| CFAG12864J | J3 / J4       | J3       | J4      |
| CFAG12864S | J3 / J4       | J3       | J4      |
| CFAG14432A | R10 / R11     | R10      | R11     |
| CFAG14432B | Parallel Only |          |         |
| CFAG14432C | R10 / R11     | R10      | R11     |
| CFAG14432D | R11 / R12     | R12      | R11     |
| CFAG14432E | R11 / R12     | R12      | R11     |
| CFAG16032C | JF2 (1-3-2)   | JF2 3-2  | JF2 3-1 |
| CFAG19232C | J3 / J4       | J3       | J4      |
| CFAG20232C | JF (1-3-2)    | JF 3-2   | JF 3-1  |

| Interface Pin Out | Parallel | SPI        |
|-------------------|----------|------------|
|                   | Vss      | Vss        |
|                   | Vdd      | Vdd        |
|                   | Vo       | Vo         |
|                   | RS       | CS         |
|                   | R/W      | MOS / SDI  |
|                   | E        | SCLK       |
|                   | DB0~DB7  | No Connect |